

Blazing Hog Firmware Upgrade - Boss Hog




Overview: The modem currently registers via 3G network first then confirms the plan type and swaps to 4G LTE service. ATT is shutting down 3G on Feb 22. We need to update the firmware on this device to register on the network via 4G LTE.


After completing the firmware upgrade(s), modem may require two updates, we will need to change 1 setting in the modem and set the APN (access point name) to connect with the correct server at ATT data centers.

It sounds like a lot... but the entire process should take less than 10 minutes.

- 1 Log into the modem. **Pro tip - this is the hardest part**
Ensure you are directly wired or connected to the modem's wifi
Open a web browser (Chrome, Edge, Safari) - in the address bar at the top - type in 192.168.1.1



This will bring up this screen



Now log in using the following:

User: admin
Pass: Securewisp01 (zero,one)

if this doesn't work after several tries.

Then try:


User: admin
Pass: admin01

finally if this doesn't work. press and hold the factory reset button until all the lights turn on - approx 20 seconds. Let go, the lights will blink wait 2 minutes


Then try:

User: admin
Pass: admin01

2 Select System on the top menu then Firmware from the drop down options



3 ALERT - uncheck "keep all setting box" -



4 Click upgrade - then repeat steps 1-4 for second update before step 5




The first upgrade removes all custom setting from the modem.

USE:
User: admin
Pass: admin01

When you log in the second time.

- 5 Open browser and goto 192.168.1.1 after two updates the log in screen looks different. Your login should now look like this.


Good to continue



The image shows a modern login interface. On the left, a blue box contains the Teltonika logo and the text "AUTHORIZATION REQUIRED" and "Please enter your username and password". On the right, there are two input fields: "Username" with "admin" entered and "Password" with "admin01" entered. A "LOG IN" button is located at the bottom right.

Login using:
User: admin
Pass: admin01


Upgrade not complete repeat steps 1-4



The image shows an older login interface. It features a black header with the Teltonika logo. Below it, the text "Authorization Required" is displayed, followed by "Please enter your username and password." There are two input fields: "Username" with "admin" and "Password" which is empty. A "Login" button is at the bottom.


old login screen.

- 6 Follow this wizard. Click Next




The image shows the "SYSTEM" configuration page in the Teltonika web interface. The "SETUP WIZARD" section is active. It includes settings for "Language" (English), "Configuration Mode" (Basic), and "Time zone" (UTC). A "SYNC WITH BROWSER" button is present. A "NEXT" button is circled in pink. The left sidebar shows navigation options like "STATES", "NETWORK", "SERVICES", and "SYSTEM".

7 Select custom APN. Type in 30691.mcs then click NEXT



8 Now just click logout you have completed the update.



Finished. You are now back online.

Please click LOGOUT